

TESTADOR E LOCALIZADOR LCD NOYafa NF-308

Código: 00175

Características:

Testa (wiremap) cabos de Rede, Telefonia, Coaxial e USB;
Verificação de erros em BNC e RJ-45, tais como, circuito aberto, curto circuito e par cruzado;
Localiza cabos de Rede, Telefonia, BNC, USB e Rede Blindado;
Mede o comprimento do cabo de Rede;
Localiza porta de Switch (portFlash);
Display Iluminado com configuração de ajuste para desligamento (economia de bateria);
Acompanha estojo com alça e fones.

Parâmetros:

Tamanho 48.8x43.5x44.5 cm

Peso 220gr

Atenção:

1. Não conectar em alta voltagem;
2. Conectar o cabo na porta correspondente ao teste desejado;
3. Leia o Manual do usuário antes de usar.

ESTADOR E LOCALIZADOR LCD NOYafa NF-308

Código: 00175

Specifications

Indictor	LCD 53x25 mm, with back light
Tone frequency	225 Hz
Max. distance of transmission	2 km
Max. distance of cable map	1 km
Max. working current	Less than 70mA
Tone mode	2 Tone adjustable
Compatible connectors	RJ11, RJ45,Coacial, USB
Max. signal voltage	15Vp-p
Function selection	3 position buttons & 1 power switch
Function and faults LCD display	LCD display (wiremap, Tone, short, , No adapter, Low battery)
Cable map indication	LCD (#1-#8)
Shielded indication	LCD (#9)
Voltage protection	AC 60V/DC 42V
Battery Type	DC9.0V (NEDA 1604/6F22 DC9V x 1pcs)
Dimension(LxWxD)	185x80x32mm
NF-308 Receiver specifications	
Frequency	225kHz
The Max. working current	Less than 70mA
Earjack	1
LED illumination	2
Battery Type	DC9.0V (NEDA 1604/6F22 DC9V) x1pc
Dimension(LxWxD)	218x46x29 mm
NF-308 Remote unit specifications	
Compatible connectors	RJ11, RJ45,Coacial, USB
Dimension(LxWxD)	107x30x24mm